

909.0054.USU

YOR920010527US1

Patent Application Papers Of:

David F. Bantz

Thomas E. Chefalas

Alexei A. Karve

Steve Mastrianni

Ajay Mohindra

For: Automatic Audio Adjustment System Based Upon A
User's Auditory Profile

**Automatic Audio Adjustment System Based Upon A User's
Auditory Profile**

BACKGROUND OF THE INVENTION

1. Field of the Invention

The present invention relates to methods and apparatus to provide for the automatic adjustment of computer-generated audio based on an audio profile of a user .

2. Description Of The Related Art

A large percentage of the population suffers from some type of hearing disorder or hearing loss. As a greater number of people live longer due to advances in health care, many of these people suffer degenerative effects of aging on the hearing process, such as the inability to filter out background noise, the inability to distinguish speech, tinnitus, and the general fall off of frequency response starting at 4Hz. Many types of hearing aids have been developed to combat these situations. A device called the Radiant Beam Array is worn around the neck as a necklace and includes an array of six microprocessors and a digital signal processor (DSP). The Starkey Cetera and Phonak Claro use a DSP to provide for altering voice over noise, similar to the way the Dolby noise reduction system works in audio. The Widex Senso-Plus uses a DSP to provide time domain processing to separate speech from background noise. All of these systems need to be configured or programmed before use, then the device is inserted in the ear.

These systems are reactive. They attempt to filter the ambient audio information to eliminate noise and provide better separation between the desired audio information

and the background noise. In some cases, these devices are preprogrammed for a particular type of environment or user, and others claim to react in real time. None of these devices are proactive. Each device must be programmed specifically for the individual. If the user loses the device, he must obtain a replacement with the same characteristics. These devices also don't work well with computer systems which emit audio suitable for mass consumption in standard frequencies, sampling rates, and nominal amplitudes.

SUMMARY OF THE INVENTION

In accordance with one aspect of the present invention, a system for adjusting audio output is provided including a transmitter unit adapted to be carried by a user and a sound generating system. The transmitter unit includes a memory and a signal transmitter. The sound generating system includes a sound generator, a signal receiver, means for altering a sound signal from the signal generator based upon a signal transmitted by the transmitter to the receiver, and at least one acoustic transducer connected to the altering means.

In accordance with another aspect of the present invention, a portable signal transmitter unit is provided comprising a battery; a signal transmitter connected to the battery for transmitting a wireless signal; and a memory connected to the signal transmitter. The memory comprises hearing information regarding a user's auditory characteristics. The signal transmitter is adapted to transmit at least a portion of the hearing information stored in the memory.

In accordance with another aspect of the present invention, a sound generating system is provided comprising a processor; a first sound generator connected to the processor; a second sound generator connected to the first sound generator by a programmable sound signal modifier; a combiner for combining an output from the second sound generator with a portion of an output from the signal modifier; and a wireless signal receiver connected to the processor. The receiver is adapted to receive a hearing information signal containing a user's auditory characteristics. The processor is adapted to configure the modifier based upon the hearing information signal received by the receiver.

In accordance with one method of the present invention, a method of altering an electrical sound signal is provided comprising steps of receiving a hearing adjustment signal from a portable transmitter, the hearing adjustment signal comprising information regarding a user's auditory characteristics; configuring a variable signal modifier based upon the received hearing adjustment signal; and transmitting the electrical sound signal through the variable signal modifier and outputting at least one altered electrical sound signal which has been altered based upon the user's auditory characteristics contained in the hearing adjustment signal.

BRIEF DESCRIPTION OF THE DRAWINGS

The foregoing aspects and other features of the present invention are explained in the following description, taken in connection with the accompanying drawings, wherein:

Fig. 1 is a block diagram of a system incorporating features of the present invention;

Fig. 2 is a block diagram of the a sound device shown in Fig. 1;

5 Fig. 3 is a block diagram of components of the computer shown in Fig. 3;

Fig. 4 is a chart of an example of a hearing profile for a person;

10 Fig. 5 is a block diagram of components of the user FOB shown in Fig. 1;

Fig. 6 is a flow chart of one method of the present invention; and.

Fig. 7 is a block diagram of an alternate embodiment of the present invention.

15 DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENT

The present invention relates to methods and apparatus to provide for the automatic adjustment of computer generated audio based on the auditory profile of a user. Referring to Fig. 1, there is shown block diagram of a system 10 incorporating features of the present invention. Although the present invention will be described with reference to the embodiments shown in the drawings, it should be understood that the present invention can be embodied in many alternate forms of embodiments. In addition, any suitable size, shape or type of elements or materials could be used.

20

25

The system 10 generally comprises a sound device 12 and a user FOB 14. In an alternate embodiment, the system 10

could comprise additional components. The sound device 12 preferably comprises a computer, such as a desktop computer, a laptop computer, or a client computer connected to a network. However, features of the present invention could be used with any suitable type of sound device including, for example, an audio stereo system or an audio mixing system.

Referring also to Fig. 2, the sound device 12 generally comprises a computer 16, speakers 18, a CD-ROM or DVD player 20, a receiver 22, a first connector 24 and a second connector 26. The computer 16 generally comprises a controller, a memory and a display. The computer could also be connected to another audio player 28, such as a keyboard or MP3 player. The first connector 24 is adapted for connecting the computer 16 to the Internet, such as a modem. The second connector 26 is adapted to connect auxiliary components to the computer 16, such as a stereo headphone set or at least one acoustic transducer. The computer, speakers, connectors and player shown in Fig. 2 are substantially conventional components with the exception of the receiver 22, certain components as shown in Fig. 3, and certain programming in the computer 16.

The computer 16 is adapted to broadcast sound from the speakers 18, or transmit sound signals to the connector 26, based upon sound signals received or read by the player 20, or connector 24, or player 28. The receiver 22 is connected to the controller or central processing unit of the computer 16. In the embodiment shown, the receiver 22 is a wireless receiver, such as a radio frequency receiver. However, in alternate embodiments, any suitable type of receiver could be used, such as an

optical receiver or an induction receiver. The receiver 22 could alternatively comprise an electrical connector, such as when the user FOB 14 comprises a mating electrical connector.

- 5 Referring also to Fig. 3, the computer 12 generally comprises the receiver 22, a central processing unit (CPU) 30, a first sound generator 32, an electrical sound signal modifier 34, a second sound generator 36 and a summation engine 38. The CPU 30 is adapted to control
- 10 the sound generator 32 to output an ordinary electrical sound signal 40. The sound generator 32 preferably comprises the player 20 and connections to the player 28 and connector 24. The sound signal 40 is preferably not amplified yet.
- 15 The output from the first sound generator 32 is connected to the modifier 34. In a preferred embodiment, the modifier 34 comprises a programmable bandpass filter and a programmable frequency shifter. However, in an
- 20 alternate embodiment, the modifier might not comprise a frequency shifter. The modifier 34 comprises two outputs 42, 44. The bandpass filter portion of the modifier 34 is adapted to separate portions of the input sound signal 40 corresponding to predetermined frequencies
- 25 ("subtracted sound") from portions of the signal 40 which do not correspond to the predetermined frequencies ("blocked sound"). In a preferred embodiment, the bandpass filter portion comprises an array of individually programmable bandpass filters. The
- 30 subtracted sound is output from the first output 42. The blocked sound is output at the second output 44. Before the separated portions of the sound signal are output at the outputs 42, 44, portions can be shifted in frequency

by the frequency shifter portion of the modifier 34 if desired.

The modifier 34 is operably controlled by the CPU 30. More specifically, the CPU 30 is adapted to send setup
 5 commands 46 to the modifier 34. In an alternate embodiment, the commands 46 could be dynamic and continuing and, not merely static initial setup commands. The set up commands 46 are used by the modifier 34 to configure it's bandpass filter portion and its frequency
 10 shifter portion as further understood from the description below.

The first output 42 is connected to the second sound generator 36. In a preferred embodiment, the second sound generator 36 comprises an amplifier. Output 48
 15 from the second sound generator 36 and the second output 44 are fed as input to the summation engine 38. The summation engine 38 is adapted to add or concatenate the two signals. The resulting signal 50 is then preferably output from the summation engine 38 to drive the sound
 20 output generator portion of the computer system's sound card or similar sound output generator.

Referring to Fig. 4, a chart of an example of a hearing profile for a person is shown. In this example, the person has a hearing degradation which is progressively
 25 worse between 1000 Hz and 8000 Hz; being very pronounced at 8000 Hz.

The modifier 34 is intended to modify the signal 40 to separate predetermined portions of the sound signal 40 into two or more portions based upon a user's hearing
 30 profile. For example, for the user profile shown in Fig. 4, the sound signal might be separated into a first

portion corresponding to the frequency range between 250-2000 Hz and a second portion corresponding to the frequency range between 2000-8000 Hz. The first portion might be output at the second output 44 unaltered. The second portion could be output at the first output 42, perhaps with a frequency shift towards the lower frequency range, to the second sound generator 36 for amplification. The two sound signal portions can then be added at the summation engine 38. In an alternate embodiment, the modifier could have more than two outputs, and the modifier could create more than two sound signal portions.

Referring also to Fig. 5, a block diagram of components of the user FOB 14 is shown. In an alternate embodiment, the user FOB 14 could comprise additional or alternative components. In this embodiment, the user FOB 14 generally comprises a memory 52, a transmitter 54, and a battery 56. The memory 52 is adapted to store information regarding the user's hearing profile therein. The transmitter 54 is preferably a low-power radio frequency transmitter. However, in alternate embodiments, any suitable type of transmitter could be provided. For example, the transmitter 54 might comprise an optical transmitter. In an alternate embodiment, the transmitter might comprise a transducer. The transmitter 54 is adapted to transmit 11 (see Fig. 1) information regarding the user's profile stored in the memory 52 of the user FOB 14 to the receiver 22 in the computer 16 of the sound device 12.

Because the transmitter 54 is preferably a low-power transmitter, the user FOB 14 must be moved into relatively close proximity with the receiver 22 before

the receiver 22 will receive the transmitted signal from the transmitter. The user FOB 14 could comprise a user actuated switch to actuate the transmitter 54. In an alternate embodiment, the transmitter 54 could be adapted to periodically transmit information from the memory 52 or could be adapted to transmit the information based upon a predetermined event, such as the transmitter 54 comprising a transceiver which receives a signal to initiate the transmit procedure.

The present invention is intended to be a proactive system. The system can provide a programmed FOB carried on the person using the computer system that is equipped with features of the present invention. The FOB can hold the information for the specific user. The data can be programmed into the FOB via the Internet, or using a computer system or wireless connection. The FOB preferably holds the user's auditory characteristics in the nonvolatile memory to prevent the loss of data in the event of a battery failure. The auditory characteristics describe the user's audio hearing profile. The information can include the profile of a user's standard hearing test performed with an audiometer. An example of the information is shown in Fig. 4.

The FOB preferably contains a low-power transmitter device that periodically broadcasts binary data representing the user's hearing profile. Because the most power is consumed during transmit, the transmitter is preferably programmed to transmit at specific time intervals. The periodic transmit allows the FOB device to operate for an extended period of time before the battery needs replacement.

When the user approaches a computer system that is enabled with the present invention, the computer system detects the transmission of the user's data from the FOB and the user's hearing profile information is sent to the computer system. The computer system reprograms the audio generation hardware and software to modify the audio output for the particular user.

For example, if the user's hearing profile shows a sharp drop-off in hearing in the 7000 to 8000 KHz range, the computer system can use a software bandpass filter to capture the corresponding range of frequencies, and amplifies them. The result can then be added back into the audio data before it is generated. The present invention can capture and cache the audio data, before the sounds are generated by the sound card, by hooking the entry point after the sound generator, but before the first amplifier stage. The audio signal can be routed through a bandpass filter array to filter the target frequencies which need amplitude and/or frequency modification. The filters are programmable such that they can be changed by an instruction sequence from the computer system. The signal passed through the bandpass filter can be amplified, attenuated, or its frequency modified by a simple amplifier and frequency shifting component. The resultant signal is then added or concatenated to the signal that was blocked by the bandpass filter, and the resulting signal is used to drive the sound output generator portion of the computer system's sound card.

The present invention can be comprised in a computer having a central processing unit which resides in the user's computer system. The central processing unit can

process internal data for delivery to the sound generator portion of the computer system by sending the sound generator a sequence or sequences of commands and data which are then used to generate the desired sound output to the speaker system. For example, if the computer system was receiving audio information from the Internet, the central processing unit would send the appropriate commands and data to the sound generator chip to allow the user to hear the audio representation of the data.

The sound generator prepares the data for output to the speakers attached to the user's computer system. The output of the sound generator is normally sent to a series of preamplifier and amplifier stages to prepare the signal for output to the speaker system. Instead of routing the signal to the preamplifier, the present invention can route the signal instead through a programmable bandpass filter/frequency shifter. The bandpass frequency is configured from the user's hearing profile obtained from the user's FOB via a low-power wireless connection. Using this information, the central processing unit can configure the characteristics of the bandpass filter.

For example, a user's hearing profile might show that the user has trouble hearing sounds in the 7000 to 8000 cycles (7-8 KHz) range, which can be separated out while the rest of the signal is sent to the summation component. If the amplitude needs to be adjusted, the signal passed through the bandpass filter can be routed through another sound generator stage where the signal is amplified. The resultant signal is then reassembled with the blocked portion at the summation engine. There, the two sound signals are merged and output to the user's

speaker, sound card or audio system. The same method can be used to adjust the frequency of the signal.

In an alternate embodiment, the computer 16 could have more or less than the two sound generators 32, 36. The computer could also have a switch to bypass the modifier 34 if no signal is received by the receiver 22, or the filters in the modifier 34 could default to an off position if no signal is received by the receiver 22. The modifier 34 could comprise merely bandpass filters without a frequency shifter, or the frequency shifter could be separate.

Referring specifically to Fig. 6, a method of the present invention can comprise determining 60 a user's hearing deficiency and programming 62 a user's FOB 14 with information regarding the hearing deficiency. When the user's FOB is moved 64 into proximity with the receiver, the data in the user FOB can be received 66 by the receiver. The central processing unit 30 can send commands to the modifier 44 to adjust 68 the filter/shifter 34. Thus, the computer 16 can automatically adjust the frequency and amplitude of sound emanating from the speakers 18 based upon a user's profile in the user FOB 14 carried by the user. The user does not need to manually adjust sound settings of the sound device 12. The adjustment is automatic. The adjustment is also configured to match the specific user's needs. The adjustment also automatically reconfigures for different users.

Referring also to Fig. 7, an alternate embodiment of the present invention could be incorporated into a hearing aid 70. The hearing aid 70 could comprise a stereo headset or other similar device. The user's FOB 14 could

transmit information 11 regarding the user's hearing profile to the hearing aid 70. The hearing aid 70 could modify sound 72 coming in, based upon the information received from the user FOB, into a modified outgoing sound 74 which adjusts the incoming sound to be more understandable or audible by the specific user. The hearing aid 70 could comprise one or more acoustic transducers, such as two acoustic transducers; one for each ear.

10 The user FOB 14 can be programmed with at least two separate user hearing profiles; such as one separate user hearing profile for each ear. Information regarding the two hearing profiles can be transmitted to the sound device such that the modifier 34 can modify the sound

15 signal 40 based upon stereo sound output or similar multi-channel (non-monophonic) sound generation. Whether the sound device is the computer 16 with speakers 18, computer 16 with a stereo headset attached to the connector 26, the hearing aid 70, or some other type of

20 sound device, the output sound can be configured for left and right side hearing variations of the individual user. Thus, if the user has a left ear that suffers from a hearing loss at 7-8 KHz, but the right ear does not suffer from this hearing loss, only the left channel of

25 the sound signal might be modified; the right channel of the sound signal could be left un-modified. A person skilled in the art, after reading this description, should be able to configure the system of the present invention for use with any suitable type of sound system.

30 Features of the present invention could be used by individual in home computers, home audio sound systems, home television/entertainment systems, automobile sound systems, headset sound players such as found in public

libraries and museums, and professional sound mixing studios, for example.

- 5 It should be understood that the foregoing description is only illustrative of the invention. Various alternatives and modifications can be devised by those skilled in the art without departing from the invention. Accordingly, the present invention is intended to embrace all such alternatives, modifications and variances which fall within the scope of the appended claims.

101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
2207
2208
2209
2210
2211
2212
2213
2214
2215
2216
2217
2218
2219
2220
2221
2222
2223
2224
2225
2226
2227
2228
2229
2230
2231
2232
2233
2234
2235
2236
2237
2238
2239
2240
2241
2242
2243
2244
2245
2246
2247
2248
2249
2250
2251
2252
2253
2254
2255
2256
2257
2258
2259
2260
2261
2262
2263
2264
2265
2266
2267
2268
2269
2270
2271
2272
2273
2274
2275
2276
2277
2278
2279
2